

**2008 VISVESVARAYA TECHNOLOGICAL UNIVERSITY**  
B.E/B.TECH COMPUTER SCIENCE ENGINEERING  
**COMPUTER NETWORKS**

TIME: 3 HOUR  
MARK: 80

**Answer ANY Five Question**  
**All Question Carry Equal Marks**

- 1 a. What is data communications? what are its characteristics? explain.
- b. Define following terms i) protocol ii) internet
- c. Describe with neat diagram the functionalities of each layer in the OSI model?
- 2 a. Calculate the Shannon channel capacity in the following cases:
- i) bandwidth = 20 kHz SNR<sub>db</sub> = 40
- ii) bandwidth = 200 kHz SNR<sub>db</sub> = 6
- b. A file contains 3 million bytes. How long does it take to download this file using a 100 kbps channel?
- c. Define line coding? describe unipolar NRZ, polar NRZ-L, bipolar AMI & Manchester encoding by applying on information sequence 101011100.
- 3 a. We have four sources, each creating 250 characters/sec. if the interleaved unit is one character and 1 synchronising bit is added to each frame, find
- i) The data rate of each source
- ii) The duration of each character in each source
- iii) the frame rate
- iv) The duration frame
- v) the no. of bits in each frame, and
- vi) the data rate of the link
- b. Define synchronous TDM
- c. Describe ASK, FSK, and PSK mechanisms and apply them over digital data 101101.
- 4 a. Briefly explain the coaxial cable and optical fibre with their applications.
- b. Explain how CRC is used in detecting errors for the following,  $g(x) = x^4 + x + 1$ . Consider the information sequence 1101011011.
- i) Find the codeword corresponding to this sequence.
- ii) If the codeword has an error in the third bit, what does the receiver obtain when it does its error checking?
- 5 a. Explain selective repeat ARQ. Justify how selective repeat ARQ outperforms Go-back-N and Stop-and-wait ARQ.
- b. Explain point-to-point protocol frame format. Also briefly describe transition phases of PPP in establishing a connection from home PC to ISP.
- 6 a. Explain the following random access protocols: i) CSMA ii) CSMA/CD

b. Explain 802.3 MAC frame format. mention the restrictions imposed on minimum and maximum lengths of a 802.3 frame.

7 a. Discuss bluetooth technology.

b. Explain the working mechanism of following devices used to connect LAN s.

8 a. What are the design goals of ATM? briefly describe ATM layers.

b. What is bit stuffing and unstuffing? Apply bit stuffing to the sequence:

011011111111100

Apply unstuffing: 01111110000111011111011111011001111110

Educationobserver.com